

DAU-2K0Z 2000W Modified Sine Wave Inverter



Remote Control Switch & Cable (optional)




Compact 2000W Modified Sine Wave Inverter

The ERAYAK DAU-2K0Z is a professional grade 2000 watts pure sine wave inverter providing up to 4000 watts of peak power. It allows you to power office equipment and most household appliances such as TVs, Fans, and mini fridges right from your car, truck, RV, or boat.



Product Features:

- Modified sine wave output
- High frequency and efficient with small size
- 100% real power
- Input & output fully isolation
- Microprocessor control system
- Smart temperature controlled cooling fan
- Sturdy and durable aluminum alloy case
- USB port for charging most mobile devices (optional type-A or C)
- Optional Remote controller
- LED status indicators
- Input protection : Reverse polarity (fuse) / Under voltage / Over voltage
- Output protection : Short circuit / Overload / Over temperature



Model	DAU-2K0Z1	DAU-2K0Z2
Continuous power	2000W	
Peak power	4000W	
No-load output voltage (@ Rated input voltage)	AC 230V +/- 10V , AC 115V +/- 10V	
Load output voltage (@ Rated input voltage)	AC 210V -240V , AC 115V +/- 10V	
Frequency	50Hz +/- 3Hz , 60Hz +/- 3Hz	
USB output (optional Type-A or C)	Type-A (DC 5V,2100mA) , Type-C (18W max.)	
Output wave	Modifies Sine Wave	
Rated input voltage	DC 13V +/- 0.2V	DC 26V +/- 0.4V
Operating voltage range	DC 11V - 15V	DC 22V - 30V
NO load current	≤0.5A	≤0.4A
Max. efficiency	≥85%	
Input low-voltage alarm	DC 10.5V +/- 0.3V	DC 21V +/- 0.4V
Input low-voltage protection	DC 9.5V +/- 0.3V	DC 19V +/- 0.4V
Input over-voltage protection	DC 16V +/- 0.3V	DC 32V +/- 0.4V
Over-load protection	2300W - 2600W	
Over Temp. protection	Yes, Shutdown output	
Output Short Circuit protection	Yes, Shutdown output	
DC Input reverse polarity	Yes, by fuse	
Operating Temp.	-15°C ~ +25°C ; 60°C @ 40% power load	
Dimension (L x W x D)	327.5*268*105mm	
Packing	color box , 2 pcs/ctn	