


DSU-600Z 600W Pure Sine Wave Inverter



PURE SINE WAVE



Battery Cable
Terminals
Black & Red



Battery Cable


Compact 600W Pure Sine Wave Inverter

The ERAYAK DAU-600Z is a professional grade 600 watts pure sine wave inverter providing up to 1200 watts of peak power. It allows you to power office equipment and most household appliances such as TVs, Fans, and mini fridges right from your car, truck, RV, or boat.



Product Features:

- Pure sine wave output
- High frequency and efficient with small size
- 100% real power
- Input & output fully isolation
- Microprocessor control system
- Smart temperature controlled cooling fan
- Sturdy and durable aluminum alloy case
- USB port for charging most mobile devices (optional type-A & type-C)
- Optional LCD display
- Input protection : Reverse polarity (fuse) / Under voltage / Over voltage
- Output protection : Short circuit / Overload / Over temperature



Model	DSU-600Z1	DSU-600Z2
Continuous power	600W	
Peak power	1200W	
No-load output voltage (@ Rated input voltage)	AC 230V +/- 10V , AC 115V +/- 10V	
Load output voltage (@ Rated input voltage)	AC 210V -240V , AC 115V +/- 10V	
Frequency	50Hz +/- 0.5Hz , 60Hz +/- 0.5Hz	
USB output (optional Type-A or C)	Type-A (DC 5V,2100mA) , Type-C (18W max.)	
Output wave	Pure Sine Wave (THD < 5%)	
Rated input voltage	DC 13V +/- 0.2V	DC 26V +/- 0.4V
Operating voltage range	DC 11V - 15V	DC 22V - 30V
NO load current	≤1.0A	≤0.6A
Max. efficiency	≥85%	
Input low-voltage alarm	DC 10.5V +/- 0.3V	DC 21V +/- 0.4V
Input low-voltage protection	DC 9.5V +/- 0.3V	DC 19V +/- 0.4V
Input over-voltage protection	DC 16V +/- 0.3V	DC 32V +/- 0.4V
Over-load protection	650W - 750W	
Over Temp. protection	Yes, Shutdown output	
Output Short Circuit protection	Yes, Shutdown output	
DC Input reverse polarity	Yes, by fuse	
Operating Temp.	-15°C ~ +25°C ; 60°C @ 40% power load	
Storage Temp. & Humidity	-30°C ~ +70°C , 10 ~ 95% RH	
Dimension (L x W x D)	272*171*74mm	
Packing	box , 5 pcs/ctn , 60*32*23.5cm	